### **ENVISION TOUCH**

## ThinKnx Envision 7 Server



Envision Touch Server is an all-in-one Touch Server able to grant the comfort of a touch user interface and the powerful features of a ThinKnx server, all in one device.

Through Envision, the end user is able to control all the installed devices, thanks to the comfortable touch screen with a low power consumption.

The main feature of the Envision touch server is the bidirectional interaction between KNX protocol and all other supported devices, such as Philips Hue, MyHome BTicino, Z-Wave, Modbus e Lutron.

Its built-in sensor board, loudspeaker and microphone enable the use of Envision as doorcom unit and thermostat at the same time.

Thanks to the integration of third-party systems, Envision can also be used as indoor station for the anti-theft system.

One single device for multiple interactions.

Order Code: ENVISION7 20

Box Dimensions: **28x22x8cm** 

Net Weight: **1,1Kg** 

Barcode: **8054633230930** 

#### Technical features:

- Octa-core Cortex A53 CPU
- Capacitive touch screen 7.0" TFT, visible area 155x87mm, 1024x600 resolution
- Suite Thinknx PRO
- Linux operating system
- KNX net/IP interface/router
- 1x native EIB/KNX port with direct connection through clips
- 1x network port
- 1x USB port
- 1x RS232 port
- 1x RS485 port
- Consumption 10W Max
- Temperature sensor
- Humidity sensor
- Ambience luminosity sensor
- Power: 12-24VDC 1.5A Max (power supply not included)

# Upgrades for Envision 7 Server



Extended report above 20MB



Security



Automation



Z-Wave



Lutron



Philips Hue



Audio/Video



Velux



Doorcom and PBX



Sonos



Legrand My Home



VAI3-10: upgrade for 3 to 10 gates



VAI11-50: upgrade for 11 to 50 gates



VAI51+: upgrade for over 51 gates



Mitsubishi gateway



3-Years warranty Extension

**GUEST ROOM MANAGEMENT - FIAS** 

## ThinKnx Fnvision 7 Client



Envision Client is a touch screen device aimed to be used with any ThinKnx Server for project visualization only. It is made from the same high-quality materials used for Envision Server. It is only equipped with an Ethernet port, a microphone and a speaker which make it ideal for an intercom client or a fancy addition to the furnishings.

Its built-in sensor board, loudspeaker and microphone enables the use of Envision as Doorcom unit and thermostat at the same time.

Order Code: ENVISION7\_C\_20

Box Dimensions: 28x22x8cm

Net Weight: **1,1Kg** 

Barcode: **8054633230947** 

### Technical features:

- Octa-core Cortex A53 CPU
- Capacitive touch screen 7.0" TFT, visible area 155x87mm, 1024x600 resolution
- Suite Thinknx PRO
- Linux operating system
- KNX net/IP interface/router
- 1x network port
- 1x USB port
- Consumption 10W Max
- Temperature sensor
- Humidity sensor
- Ambience luminosity sensor
- Power: 12-24VDC 1.5A Max (power supply not included)